

## Mixers

### MPX-1/BK

Number 20.2170

#### Stereo DJ mixer

- 2 stereo input channels, each with gain control and 2-way equalizer, switchable phono/line
- DJ microphone channel with talkover, manually selectable
- Pre-fader listening (PFL) to the stereo input channels via adjustable headphone output
- Replaceable crossfader for crossfading between the two input channels
- Especially easy-sliding HQ faders with additional guides
- Stereo LED level display



## Technical Facts Mixers

### Inputs

Mic, mono 1.5mV

Phono, stereo 3mV

Line, stereo 150mV

### Outputs

Master, stereo 1V/600Ω

Record, stereo 0.5V/600Ω

Headphones, stereo 8Ω

Frequency range 20-20,000Hz

THD 0.1%

### S/N ratio

Line 61dB

Phono 56dB

Mic 49dB

### Equalizer

Bass ±12dB/50Hz

Treble ±12dB/10kHz

Talkover -16dB

Power supply 12V~/700mA via  
suppl. plug-in PSU

Admiss. ambient temp. 0-40 °C

Dimensions 164x218x77mm

Weight 1.2kg